

Print Utility for Android Operating Environment

Operating Environment of Print Utility for Android

Item	Description
Network Protocol	LPD
Tested devices & OS versions	Google Pixel (Android™ 9.0) SONY Xperia XZ3 (Android™ 9.0) Huawei Nexus6P (Android™ 8.1.0) Huawei P20 lite (Android™ 8.1.0) OPPO R15 Neo (Android™ 8.1.0) HTC Nexus9 (Android™ 7.1.1) Samsung Galaxy S6 (Android™ 7.0) Samsung Galaxy S8 (Android™ 7.0) LG Nexus5 (Android™ 6.0.1) Xiaomi Mi 5 (Android™ 6.0.1) Samsung Galaxy S4 (Android™ 5.0)
Supported Languages	English, Chinese (Simplified / Traditional), Korean, Japanese, Thai, Vietnamese, Indonesian
Features	Printing from application Printing web pages Printing photos saved in the photo album Printing photos taken by the internal camera Linking with Cloud Service Hub Printing DocuWorks and PDF documents Printing from Application Working with ApeosWare Management Suite Server-less On-Demand Print Scan from scanner Linking with NFC
Print settings	Printing photo/ image/website Specify the number of copies (max 99) Paper size: A3, A4, Letter, A5, B4, B5, 4 x 6" (101.6 x 152.4 mm), 8.5 x 14", 11 x 17", 2L-size (127 x 178 mm), Postcard (100 x 148 mm) Image orientation: Portrait / Landscape Output Color: On / Off 2-sided print: On / Off Pages Per Sheet: 2 Pages Up / 4 Pages Up / 8 Pages Up / 16 Pages Up / 32 Pages Up (32 Pages up only for printing from photo gallery) Stapling: Off / 1 Staple Top Left Paper tray: Automatically Select / Bypass tray Paper type: Plain / Heavy weight / Heavy weight Reload Authentication and Accounting
	For PDF/ DocuWorks documents Specify the number of copies (max 99) Paper size: Same as Paper Size, A4, A3, A5, B4, B5, Letter, Legal, 11 x 17", Postcard (100 x 148 mm)

Item	Description
	Collated: On / Off Output Color: On / Off 2-sided print: 1sided Print / 2sided Print / 2sided, Flip on short Edge Pages Per Sheet: 2 Pages Up / 4 Pages Up Stapling: Off / 1 Staple Top Left Hole Punch: No hole punch, 2-hole punch, 3-hole punch, 4-hole punch Paper tray: Automatically Select / Bypass tray Authentication and Accounting
Scanner settings	[Scan Size] A4 / Letter [Resolution] 200 dpi / 300 dpi [Image Type] Full Colour / Grayscale [File Format] JPEG / PDF / DocuWorks
Printer settings	Specifying an IP address directly ^{*1} Searching for a printer by using Bonjour ^{*2 *3} Searching for a printer using Wi-Fi Direct ^{*4 *5 *6}

- *1: An IP address and port number must have been specified on the multifunction printer or printer.
- *2: An IP address and port number must have been specified on the multifunction printer or printer, and Bonjour must be running.
- *3: Search with Bonjour is not available when accessing from the secondary Ethernet of MFD.
- *4: Wi-Fi Direct must be enabled on the multifunction device or printer.
- *5: This search feature cannot be used for multifunction devices or printers that are connected to a wireless LAN converter.
- *6: For the following models, the group setting in Wi-Fi Direct settings must be changed to Auto, and the Wi-Fi status must be Not Connected.
 - DocuPrint CM315 z/CM318 z
 - DocuPrint CM405 df
 - DocuPrint CP315 dw/CP318 dw
 - DocuPrint CP405 d
 - DocuPrint M355 df
 - DocuPrint M455 df
 - DocuPrint P355 d
 - DocuPrint P365 d
 - DocuPrint P368 d
 - DocuPrint P455 d
 Products for sale may differ according to country or region. For more information, please contact the Fuji Xerox office or authorized dealers in each country/region.