

## AUDITRON FOR B.E.A.R

### 1. Set Password

Press **xxxxxx**

Press **Enter** ↵

[ **Accounts Menu** ] Press **Enter** ↵

[ **Add Field Menu** ] Press **Enter** ↵

\* [ **1<sup>st</sup> field** ] Press **Enter** ↵

[ **Input Details** ] Key in **password xxxx**

Press **Enter** ↵

[ **Limit** ] Key in **999999**

Press **Enter** ↵

Repeat \* or Press Delete ( 3 times ) to exit

### 2. Read Copy Count

Press **xxxxxx**

Press **Enter** ↵

[ **Accounts Menu** ] Press **Enter** ↵

[ **Add field Menu** ] Press ▼ ( 2 times )

[ **View Usage** ] Press **Enter** ↵

[ **By P.I.N Number** ] Press **Enter** ↵

[ **All or One** ] Select ▼ - All or **Enter** ↵- **One**

Press **Enter** ↵

Press ▼ to Scroll through accounts

Press **Delete** ( 3 times ) to exit

### 3. Reset Copy Count

Press **xxxxxx**

Press **Enter** ↵

[ **Accounts Menu** ] Press **Enter** ↵

[ **Add field Menu** ] Press ▼ ( 3 times )

[ **Delete Menu** ] Press **Enter** ↵

[ **Zero Usage** ] Press **Enter** ↵

[ **All or One** ] Select ▼ - All or **Enter** ↵- **One**

Press **Enter** ↵

[ **Are You Sure** ] Press 1 - **Yes** or **Enter** ↵- **No**

Press **Delete** ( 3 times ) to exit

**4. Delete Pin Numbers**

Press **xxxxxx**

Press **Enter** ↵

[ **Accounts Menu** ] Press **Enter** ↵

[ **Add field Menu** ] Press ▼ ( 3 times )

[ **Delete Menu** ] Press **Enter** ↵

[ **Zero Usage** ] Press ▼

[ **Delete field/fields** ] Press **Enter** ↵

[ **By Pin Number** ] Press **Enter** ↵

[ **All or One** ] Select ▼ - **All** or **Enter** ↵- **One**

[ **Input Details** ] Key in **password xxxx** to be deleted

Press **Enter** ↵

[ **Are You Sure** ] Press 1 - **Yes** or **Enter** ↵- **No**

Press 1

Press **Delete** ( 3 times ) to exit

**5. Print Copy Usage (Note: only print through serial port)**

Press **xxxxxx**

Press **Enter** ↵

[ **Accounts Menu** ] Press **Enter** ↵

[ **Add field Menu** ] Press ▼ **Enter** ↵

Press ▼ ( 1 time )

[ **Print Menu** ] Press **Enter** ↵

[ **Print Usage** ] Press **Enter** ↵

[ **Pin Number** ] Press **Enter** ↵

[ **All o One** ] Select ▼ - **All** or **Enter** ↵- **One**

Press **Delete** ( 3 times ) to exit

Press **Enter** ↵