

User Instruction Guide to change stored fax numbers for Model :3006

Print out the telephone directory report for reference before making changes

Changing the Directory numbers

1. Press DIRECTORY SETUP.
2. Press ENTER to select individual.
3. Enter the directory code: from 1 – 100
4. Press ENTER.
5. You can now enter the telephone number with the prefix digit 6.
6. Press ENTER
7. Enter the name of the remote station (1-16 characters)
8. Press ENTER
9. To end the procedure, press ENTER to select NO. Now you can program another entry or press STOP to go to standby.