

User Instruction Guide to change stored fax numbers for Model :7033

Print out the telephone directory report for reference before making changes

Print Dial Directory Report

1. Open the Access Panel
2. DIAL DIRECTORY REPORT
3. Press ENTER

Change Dial Directory Numbers

1. Press [Directory Setup]
2. Enter Directory # - (001 – 150) Press [Enter].
3. Enter the 8 digit number to call. Press [Enter].
4. Enter Remote Name. Press [Enter].
<Special Feature> or <Next Directory Number>
Press [Select]
5. Press [Enter].
6. To continue with new directory, perform the above steps again.
7. Press [Exit].

Change Local Terminal ID

1. Press [Terminal Setup]
2. Select <Local Terminal> Press [Enter].
3. Enter Fax Telephone number with the prefix digit 6.
Press [Enter].
4. Press [Exit].